


PEPWAVE | AP ONE AX



Better Coverage and Speed with Wi-Fi 6

Deploy Anywhere, Manage Centrally

Turnkey or Custom Captive Portals

Enterprise-Grade Fast Roaming

Seamless Peplink SD-WAN Integration

Manage Centrally, No Extra Hardware Needed

SSID Management

SSID	Security	SSID Visibility	Radio Selection
Production	WPA2 - Personal	✓	2.4 GHz band only
_Guest_2_4G	WPAWPA2 - Personal	✓	2.4 GHz band only
_Guest_5G	WPA2 - Personal	✓	5 GHz band only
Production_11a	WPA2 - Personal	✓	5 GHz band only
Wireless	WPA2 - Personal	✓	2.4 GHz band only
Wireless_11a	WPA2 - Personal	✓	5 GHz band only
Balance	WPA2 - Personal	✓	2.4 GHz band only
Balance_11a	WPA2 - Personal	✓	5 GHz band only

Usage Report

Data Usage: Hourly Daily Monthly Unit: MB GB TB

Device Selection: All By products By tags

Daily Report

Daily Usage

Day	Download	Upload	Total
2020-07-13	52.90 GB	17.21 GB	70.11 GB
2020-07-12	14.86 GB	0.67 GB	15.54 GB
2020-07-11	15.34 GB	0.67 GB	16.01 GB

Searchable Event Log

Type	Details
system	Time synchronization successful
system	Time synchronization fail
system	Time synchronization successful
system	Time synchronization fail
system	Changes applied
system	Changes applied
system	InControl has updated the configuration as tags were updated
system	Wi-Fi Configuration has been updated by InControl
system	InControl has updated the configuration as tags were updated

Each AP One AX comes equipped with InControl central management. View the health and data usage of your network from any web browser. Centrally manage your

network's SSID and radio settings from a single pane of glass. Use the searchable event log to quickly diagnose your entire network.

Turnkey or Custom Captive Portals

Splash Screen

Title Text: Fullbright International Wi-Fi

Title Text Color: #C2C2C3

Header Color: #333333

Background Color (behind tabs): #E6E6E6

Active Tab Text Color: #000000

Inactive Tab Text Color: #000000

General Description: Thanks for using the free Wi-Fi service

General Description Alignment: Auto Left Center Right

General Text Color: #000000

General Button Text Color: #FFFFFF

General Button and Link Color: #2B8ACB

Footer Color: #000000

Splash Screen Signed-in Screen

Fullbright International Wi-Fi

Thanks for using the free Wi-Fi service

Free Internet for Social Network Users!

I have read and agree to the [terms and conditions](#)

I agree for Fullbright International to store and use my personal information for marketing communications, market research, advertisement and identifying other products/services which might be of interest to me. I agree for Peplink store my personal information to help Fullbright International to use my personal information for the above-mentioned purposes.


I consent to the [privacy policy](#)

[Sign in with Facebook](#)

[Sign in with Google](#)

Customize your captive portal as little or as much as you would like. Right out of the box, it includes a captive portal ready for immediate use.

For a more branded user experience, you can edit every aspect of the captive portal using InControl.



Simply Better Wi-Fi

Wi-Fi 6: Faster, Better

This technology is 45% faster than Wi-Fi 5, has 4x more device capacity, and consumes less power for connected devices.

Enterprise-Grade Fast Roaming

This device supports 802.11k, v, and r, providing users with a more seamless roaming experience between access points.



Seamless Peplink SD-WAN Integration

The AP One AX works seamlessly with other services in the Peplink ecosystem, providing

unique network capabilities, unmatched network flexibility and ease of use.

InControl Central Management

Monitor network health on a single dashboard. Push configuration profiles on multiple devices at once. Remotely access the Web Admin of any device.

Balance/MAX/FusionHub


Provides unbreakable connectivity by combining multiple WANs. Works with InControl to centralize VLAN, firewall, and outbound policy.

SD-Switch



Works with InControl to remotely configure and activate PoE ports. Monitor power consumption.

AP One

Works with InControl to centralize SSIDs, radio settings, and deliver captive portals.



Product Code	APO-AX
Ethernet Port	1x 2.5 Multigigabit Ethernet
Wi-Fi Standard	1x 2.4Ghz 802.11b/g/n/ax 1x 5Ghz 802.11a/n/ac/ax
Data Rates	4X4 MU-MIMO 2.4 GHz: up to 1148 Mbps 5 GHz: up to 2400 Mbps
Channel Width	20/40/80 MHz
Recommended Concurrent Users per Radio	256
SSID Per Radio	16
Transmit Power	2412 – 2472 MHz: up to 17dBm 5180 – 5825 MHz: up to 17dBm
Included Antenna	Built-in Omni Antenna Antenna gain: 2.7 – 5dBi for 2.4GHz, 3.8 – 5.6dBi for 5GHz
Enclosure	Plenum-rated, Indoor Plastic
Dimensions	8.1 x 8.1 x 1.3 inches 205 x 205 x 32 mm
Weight	1.73 pounds 785 grams
Power Input	DC Jack: 12V DC AC Adapter: AC Input 100V – 240V, DC Output 12V, 3A* 802.3 at PoE #
Power Consumption	24W (max.)
Operating Temperature	32° - 104°F 0° - 40°C
Certifications	FCC, CE, RoHS
Warranty	1 Year Limited Warranty



* Optional feature.
PoE Injector is available separately.

- Network**
- Bridge Mode
 - Router (NAT) Mode
 - Wireless Distribution System (WDS)
 - Support for PPPoE, Static IP, DHCP
 - Management VLAN
 - Spanning Tree Protocol

- AP Security**
- Open
 - WPA/WPA2/WPA3-Personal
 - WPA/WPA2-Enterprise

- Device Management**
- Web Administrative Interface
 - InControl Cloud Management
 - Peplink AP Controller
 - SNMP v1, v2c and v3

- Radio**
- Multiple SSID
 - Auto Channel Selection
 - Transmit Power Adjustment
 - Neighbor AP Detection

- Client Management**
- Per SSID
 - VLAN with QoS (802.1p/802.1q)
 - Bandwidth Control
 - MAC Address Filtering
 - Layer 2 Client Isolation
 - Limit on Max. Number of Client
 - Per Client
 - VLAN with RADIUS
 - VLAN with VLAN Pool
 - Bandwidth Control
 - Multicast Filter
 - IGMP Snooping/Multicast Enhancement

- Captive Portal by InControl**
- Package Contents**
- AP ONE AX
 - Ceiling Mount
 - Screw Kit

Ordering Information

Product Code	Description
APO-AX	4x4 MIMO Wi-Fi 6 AP for Business, manageable by InControl 2. Simultaneous Dual-Band 802.11ax/ac/b/g/n

Add-on Feature

Product Code	Description
ACW-107	802.3af/at PoE Injector. Compatible with MAX Hotspot and AP One AX
ACW-602	1x12V3A Power Supply. Compatible with MAX HD2 and AP One AX